宗申动力 ZONG SHEN POWER	**BQH4000**
	3.8kw Inverter Generator
	Recoil Start

Appearance	**BQH4000 3.8kw Inverter Generator Specs**	
	Generator Type	**Inverter**
	Alternator Material	**Permanent Magnet**
	Frequency (Hz)	**50**
	Voltage (V)	**230**
	THD (%)	**<3**
	Max Output (kw)	**3.8**
	Rated Output (kw)	**3.6**
	Run Time @ 50% load (hrs)	**7**
	Fuel Tank Capacity (L)	**7.8**
	Noise (dBA)	**≤70**
	Net Weight (kg)	**32.5**
	Packing Size (cm)	**65x37x61**
	Engine	
	NH225-2	
	Displacement (cc)	**224**
	Bore × stroke (mm)	**72x55**
	Oil quantity (cc)	**0.6**
	Recommended oil	**10w-40/10W-30**
	Fuel tank volume (cc)	**2800**
	Starting System	**Recoil**
	Rated power (kW/rpm)	**4.5/3600**
	Max torque (N • m/rpm)	**12.5**
	Fuel type (octane RON)	**91**
	Certification	**EPA**
	Endurance Validation (h)	**500**
	Choke control	**Manual**
	Flameout method	**Manual Stop Switch**
	Oil alarm	**Y**
*Pictures shown are for illustration purpose only.		